



Camera Security / **SuperLink Sensors**

Motion Sensor



^ Overview

Dimensions

Device with wall mount:

93.5 x 22.5 x 24.7 mm (3.7 x 0.89 x 0.97")

Device with corner mount:

93.5 x 22.5 x 27.9 mm (3.7 x 0.89 x 1.1")

Mounting

Adhesive and screw mount

UniFi Application Suite

Protect

^ Performance

Connectivity

SuperLink (Proprietary)

Operating Frequency

US	915.6–927.6 MHz
EU	865.1–869.5 MHz

Antenna Gain

SuperLink	1 dBi
-----------	-------

Max. TX Power

SuperLink	14 dBm
-----------	--------

Max. Range

SuperLink	2 km (1.2 mi)
-----------	---------------

Sensor Features

Horizontal PIR Sensor	Detection range up to 1.5 m (4.9 ft)
Vertical PIR Sensor	Detection range up to 6 m (19.7 ft) with pet immunity

^ Hardware

Max. Power Consumption	22.6mW
Supported Voltage Range	3V
Power Method	Lithium battery CR123A
Battery Life	Up to 6 years
Weight	45 g (1.6 oz)
Enclosure Material	Polycarbonate, high-density polyethylene (HDPE)
Mount Material	Polycarbonate
Buttons	(1) Factory-reset (1) Function button (1) Tamper switch
LEDs	(1) Status: R/B/W (1) Signal: B/R
Ambient Operating Temperature	0 to 40° C (32 to 104° F)
Ambient Operating Humidity	10 to 90% noncondensing
Certifications	FCC, IC, CE
NDAA Compliant	✓

^ Software

Application Requirements	
— Web Application	UniFi Protect
— Mobile App	UniFi Protect iOS™ and Android™

